

MAP Expansion Enclosure Kit

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Suitable for a power supply, 2x 18 Ah batteries and 2x LSN gateways
- ▶ Expands the MAP system

The MAP Expansion Enclosure Kit contains one MAP Expansion Enclosure, one MAP Expansion Enclosure Tamper Switch, one MAP Enclosure Lockset, and one MAP AC Terminal Block. The Expansion Enclosure can house the MAP Power Supply 150W and up to two 18 Ah batteries or four MAP LSN Gateways. It fits in 48 cm (19 in.) mounting.

- 1 Accessory pack
 - 1 MAP Expansion Enclosure Tamper Switch (ICP-MAP0055)
 - 1 MAP AC Terminal Block (ICP-MAP0065)
 - 1 MAP Enclosure Lockset (ICP-MAP0060)
- 1 Hardware pack
 - 7 TORQ screws (M4 x 8mm, Type A)
- 1 Literature – Installation Template

Certifications and approvals

Region	Certification	
Austria	VSOE	W 160215/61 E, VSOE Class WS
	VSOE	W 160215/62 E, VSOE Class WS
Germany	VdS	G114050 ICP-MAP0120
Europe	CE	EN 55022, EN 50130-4, EN 6100-3-2, EN 6100-3-3, EN 60950-1 MAP 5000 family
Poland	TE-CHOM	03-16-o ICP-MAP5000

Parts included

Quant.	Component
1	Enclosure assembly

Technical specifications

Mechanical

Dimension in cm (H x W x D)	43.6 x 44.3 x 11.2
Weight in g	780
Material	1.5 mm cold rolled steel
Color	White

Environmental

Protection class	IP30
Security level	IK06

Environmental class	II: EN50130-5, VdS 2110
Usage	Indoor

Ordering information

MAP Expansion Enclosure Kit

Contains one MAP Expansion Enclosure, one MAP Expansion Enclosure Tamper Switch, one MAP Enclosure Lockset, and one MAP AC Terminal Block.
Order number **ICP-MAP0120**

Accessories

MAP Hinged Mounting Plate

Fits inside the MAP Panel Enclosure or the MAP Expansion Enclosure and holds up to six system modules
Order number **ICP-MAP0025**

MAP Accessory Mounting Plate

Accessory mounting plate which can carry up to two MAP 12V Converters and one SIV Fuse Plate or an AT 2000 module.
Order number **ICP-MAP0020**

MAP Accessory Mounting Plate EMIL

Accessory mounting plate which can carry one ISP-PCBA-EMIL and either one relay module IMS-RM or one voltage transformer ICP-MAP0017. It is also suitable for all standard 3-hole accessory modules.
Order number **ICP-MAP0021**

MAP Expansion Enclosure Tamper Switch

Fits in the MAP Expansion Enclosure
Order number **ICP-MAP0055**

SIV 28 Fuse Distributor

For monitored fusing of the devices connected to a panel like e.g. MAP5000, up to 5 fuses
Order number **SIV 28**

MAP AC Terminal Block

Terminal block to connect supply voltage to the MAP power supply 150W.
Order number **ICP-MAP0065**

MAP Rack Mounting Kit

Brackets and fasteners for preparing the MAP Expansion Enclosure for rack mounting. Fasteners for mounting to rack **not** included.
Order number **ICP-MAP0035**

MAP Enclosure Lockset

Lock, two keys, and two warranty seals for use on MAP Panel Enclosure, MAP Power Enclosure, or MAP Expansion Enclosure.
Order number **ICP-MAP0060**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia