

MAP Panel Enclosure Kit

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Suitable for a main panel, a DE module, a power supply, 2x 40 Ah batteries and 4x LSN gateways
- ▶ Includes a hinged mounting plate

The MAP Panel Enclosure Kit (ICP-MAP0111) contains one MAP Panel Enclosure, one MAP Hinged Mounting Plate, one MAP Panel Enclosure Tamper Switch, one MAP Enclosure Lockset, and one MAP AC Terminal Block.

Certifications and approvals

Region	Certification	
Germany	VdS-S	S 112016 C MAP 5000
	VdS	G111040 ICP-MAP-5000
	VdS	G114801 ICP-MAP5000-COM
Europe	CE	EN 55022, EN 50130-4, EN 6100-3-2, EN 6100-3-3, EN 60950-1 MAP 5000 family
	EN5013 1	EN-ST-000121 MAP 5000
France	AFNOR	NF&A2P Grade 3, Certificat numéro 1133400003A0, Conforme à la norme NF324-H58

Parts included

Quant.	Component
1	Enclosure assembly
1	Accessory pack <ul style="list-style-type: none"> • 1 MAP Panel Enclosure Tamper Switch (ICP-MAP0050) • 1 MAP AC Terminal Block (ICP-MAP0065) • 1 MAP Enclosure Lockset (ICP-MAP0060)
1	Hardware pack <ul style="list-style-type: none"> • 7 TORX screws (M4 x 8 mm, Type A) • 2 TORX screws (M3 x 5 mm) • Spiral wrap (large size)
1	Literature – Installation Template
1	Drill template

Technical specifications

Mechanical

Dimension in cm (H x W x D)	65.8 x 44.3 x 19.35
Dimension in inch (H x W x D)	25.9 x 17.4 x 7.6
Weight in g	1566

Material	1.5 mm (0.06 in.) cold rolled steel
Color	White

Environmental

Protection class	IP30 IP31 (with an edge protection profile)
Security level	IK06
Environmental class	II: EN50130-5, VdS 2110
Usage	Indoor

Ordering information

MAP Panel Enclosure Kit

Kit contains one MAP Panel Enclosure, one MAP Hinged Mounting Plate, one MAP Panel Enclosure Tamper Switch, one MAP Enclosure Lockset, and one MAP AC Terminal Block.

Order number **ICP-MAP0111**

Accessories

MAP Accessory Mounting Plate

Accessory mounting plate which can carry up to two MAP 12V Converters and one SIV Fuse Plate or an AT 2000 module.

Order number **ICP-MAP0020**

MAP Accessory Mounting Plate EMIL

Accessory mounting plate which can carry one ISP-PCBA-EMIL and either one relay module IMS-RM or one voltage transformer ICP-MAP0017. It is also suitable for all standard 3-hole accessory modules.

Order number **ICP-MAP0021**

MAP Panel Enclosure Tamper Switch

Fits in the MAP Panel and MAP Power Enclosures.

Order number **ICP-MAP0050**

SIV 28 Fuse Distributor

For monitored fusing of the devices connected to a panel like e.g. MAP5000, up to 5 fuses

Order number **SIV 28**

MAP AC Terminal Block

Terminal block to connect supply voltage to the MAP power supply 150W.

Order number **ICP-MAP0065**

MAP Spare Cable Kit

Cable kit containing cables and parts for electrical connections of MAP devices.

Order number **ICP-MAP0090**

MAP Enclosure Lockset

Lock, two keys, and two warranty seals for use on MAP Panel Enclosure, MAP Power Enclosure, or MAP Expansion Enclosure.

Order number **ICP-MAP0060**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com